

Get a Quote

Overview

The Cisco Catalyst 9120AX Series Access Points are the next generation of enterprise access points. They are resilient, secure, and intelligent. C9120AXI-B is the Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, B Domain.

Quick Specification

Figure 1 shows the appearance of C9120AXI-B.



Table 1 shows the quick specification of C9120AXI-B.

Product Code	C9120AXI-B
Description	Cisco Catalyst 9120AXI Series, B Domain
Software	<ul style="list-style-type: none"><li>• Cisco Unified Wireless Network Software Release 8.9.x or later</li><li>• Cisco IOS® XE Software Release 16.11 with AP Device Pack, or later</li></ul>
Supported wireless LAN controllers	<ul style="list-style-type: none"><li>• Cisco Catalyst 9800 Series Wireless Controllers</li><li>• Cisco 3500, 5520, and 8540 Series Wireless Controllers and Cisco Virtual Wireless Controller</li></ul>
Dimensions (W x L x H)	8.5 x 8.5 x 1.7" (21.6 x 21.6 x 4.3 cm)
System memory	<ul style="list-style-type: none"><li>• 2048 MB DRAM</li><li>• 1024 MB flash</li></ul>
Frequency band and 20-MHz operating channels	<p>B (B regulatory domain):</p> <ul style="list-style-type: none"><li>• 2.412 to 2.462 GHz; 11 channels</li><li>• 5.180 to 5.320 GHz; 8 channels</li><li>• 5.500 to 5.700 GHz; 11 channels</li><li>• 5.745 to 5.865 GHz; 7 channels</li></ul>

## Product Details

### Supported Platforms

Table 2 shows the supported platforms and software.

Supported wireless LAN controllers and Software	Recommended Model
Cisco 3500 Series Wireless Controllers	<a href="#">AIR-CT3504-K9</a>
Cisco 5520 Series Wireless Controllers	<a href="#">AIR-CT5520-K9</a>
Cisco 8540 Series Wireless Controllers	<a href="#">AIR-CT8540-K9</a> AIR-CT8540-1K-K9
Cisco 9800 series Wireless Controllers	C9800-40-K9 C9800-80-K9
Cisco Virtual Wireless Controller	/
Cisco Unified Wireless Network Software Release 8.9 or later	/
Cisco IOS ® XE Software Release 16.11 or later	/

### Compare to Similar Items

Table 3 shows the comparison of Cisco AP 9120I series.

SKU	Description
<a href="#">C9120AXI-A</a>	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, A Domain
C9120AXI-B	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, B Domain
C9120AXI-B-EDU	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, B Domain
C9120AXI-D	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, D Domain
<a href="#">C9120AXI-E</a>	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, E Domain
<a href="#">C9120AXI-H</a>	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, H Domain
C9120AXI-I	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, I Domain
C9120AXI-K	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, K Domain
C9120AXI-Q	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, Q Domain
C9120AXI-S	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, S Domain
C9120AXI-Z	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, Z Domain

## Get More Information

Do you have any question about the C9120AXI-B?

Contact us now via [info@hi-network.com](mailto:info@hi-network.com).

## Specification

C9120AXI-B Specification	
Description	Cisco Catalyst 9120AX Access Point, internal antennas; Wi-Fi 6; 4x4:4 MIMO, B Domain
Software	<ul style="list-style-type: none"> <li>• Cisco Unified Wireless Network Software Release 8.9.x or later</li> <li>• Cisco IOS ® XE Software Release 16.11 with AP Device Pack, or later</li> </ul>
Supported wireless LAN controllers	<ul style="list-style-type: none"> <li>• Cisco Catalyst 9800 Series Wireless Controllers</li> <li>• Cisco 3500, 5520, and 8540 Series Wireless Controllers and Cisco Virtual Wireless Controller</li> </ul>
802.11n version 2.0 (and related) capabilities	<ul style="list-style-type: none"> <li>• 4x4 MIMO with four spatial streams</li> <li>• Maximal Ratio Combining (MRC)</li> <li>• 802.11n and 802.11a/g beamforming</li> <li>• 20- and 40-MHz channels</li> <li>• PHY data rates up to 890 Mbps (40 MHz with 5 GHz and 20 MHz with 2.4 GHz)</li> <li>• Packet aggregation: A-MPDU (transmit and receive), A-MSDU (transmit and receive)</li> <li>• 802.11 Dynamic Frequency Selection (DFS)</li> <li>• Cyclic Shift Diversity (CSD) support</li> </ul>
802.11ac	<ul style="list-style-type: none"> <li>• 4x4 downlink MU-MIMO with four spatial streams</li> <li>• MRC</li> <li>• 802.11ac beamforming</li> <li>• 20-, 40-, 80-, and 160-MHz channels</li> <li>• PHY data rates up to 3.47 Gbps (160 MHz with 5 GHz)</li> <li>• Packet aggregation: A-MPDU (transmit and receive), A-MSDU (transmit and receive)</li> <li>• 802.11 DFS</li> <li>• CSD support</li> </ul>
802.11ax	<ul style="list-style-type: none"> <li>• 4x4 downlink MU-MIMO with four spatial streams</li> <li>• Uplink/downlink OFDMA</li> <li>• TWT</li> <li>• BSS coloring</li> <li>• MRC</li> <li>• 802.11ax beamforming</li> <li>• 20-, 40-, 80-, and 160-MHz channels</li> <li>• PHY data rates up to 5.38 Gbps (160 MHz with 5 GHz and 20 MHz with 2.4 GHz)</li> <li>• Packet aggregation: A-MPDU (transmit and receive), A-MSDU (transmit and receive)</li> <li>• 802.11 DFS</li> <li>• CSD support</li> </ul>
Integrated antenna	Flexible radio (either on 2.4GHz or on 5GHz) <ul style="list-style-type: none"> <li>• 2.4 GHz, peak gain 4 dBi, internal antenna, omnidirectional in azimuth</li> </ul>

	<ul style="list-style-type: none"> <li>• 5 GHz, peak gain 5 dBi, internal antenna, omnidirectional in azimuth</li> </ul> Dedicated 5GHz radio <ul style="list-style-type: none"> <li>• 5 GHz, peak gain 4 dBi, internal antenna, omnidirectional in azimuth</li> </ul>
External antenna (sold separately)	<ul style="list-style-type: none"> <li>• Cisco Catalyst 9120E Access Points are certified for use with antenna gains up to 6 dBi (2.4 GHz and 5 GHz)</li> <li>• Cisco Catalyst 9120P Access Points are certified for use with antenna gains up to 13 dBi (2.4 GHz and 5 GHz) with the AIR-ANT2513-P4M-N= antenna</li> <li>• Cisco offers the industry's broadest selection of antennas, delivering optimal coverage for a variety of deployment scenarios</li> <li>• Supports Self-Identifiable Antennas (SIA) on one RP-TNC port</li> </ul>
Smart Antenna Connector	<ul style="list-style-type: none"> <li>• Available on the 9120E and on the 9120P only</li> <li>• Compact multi RF connector with DART interface</li> <li>• Requires the AIR-CAB002-DART-R= 2 ft smart antenna connector when used with antennas with RP-TNC connector</li> <li>• Required when running the flexible radio as either a second 5-GHz serving radio or a Wireless Security Monitoring radio</li> </ul>
Interfaces	<ul style="list-style-type: none"> <li>• 1x 100, 1000, 2500 Multigigabit Ethernet (RJ-45) – IEEE 802.3bz</li> <li>• Management console port (RJ-45)</li> <li>• USB 2.0 @ 3.75W (enabled via future software)</li> </ul>
Indicators	<ul style="list-style-type: none"> <li>• Status LED indicates boot loader status, association status, operating status, boot loader warnings, and boot loader errors</li> </ul>
Dimensions (W x L x H)	<ul style="list-style-type: none"> <li>• Access point (without mounting brackets): C9120I: 8.5 x 8.5 x 1.7" (21.6 x 21.6 x 4.3 cm)</li> </ul>
Input power requirements	<ul style="list-style-type: none"> <li>• 802.3at Power over Ethernet Plus (PoE+), 802.3bt Cisco Universal PoE (Cisco UPOE+, Cisco UPOE®)</li> <li>• Cisco power injector, AIR-PWRINJ6=</li> <li>• 802.3af PoE</li> <li>• Cisco power injector, AIR-PWRINJ5= (Note: This injector supports only 802.3af)</li> </ul>
Environmental	Cisco Catalyst 9120AXI <ul style="list-style-type: none"> <li>• Nonoperating (storage) temperature: -22° to 158°F (-30° to 70°C)</li> <li>• Nonoperating (storage) altitude test: 25°C, 15,000 ft.</li> <li>• Operating temperature: 32° to 122°F (0° to 50°C)</li> <li>• Operating humidity: 10% to 90% (noncondensing)</li> <li>• Operating altitude test: 40°C, 9843 ft.</li> </ul>
System memory	<ul style="list-style-type: none"> <li>• 2048 MB DRAM</li> <li>• 1024 MB flash</li> </ul>
Available transmit power settings	2.4 GHz <ul style="list-style-type: none"> <li>• 23 dBm (200 mW)</li> <li>• 20 dBm (100 mW)</li> <li>• 17 dBm (50 mW)</li> <li>• 14 dBm (25 mW)</li> <li>• 11 dBm (12.5 mW)</li> <li>• 8 dBm (6.25 mW)</li> <li>• 5 dBm (3.13 mW)</li> <li>• 2 dBm (1.56 mW)</li> <li>• -1dBm (0.79mW)</li> <li>• -4dBm(0.39mW)</li> </ul> 5 GHz <ul style="list-style-type: none"> <li>• 26 dBm (400 mW)</li> <li>• 23 dBm (200 mW)</li> <li>• 20 dBm (100 mW)</li> <li>• 17 dBm (50 mW)</li> </ul>

	<ul style="list-style-type: none"> <li>• 14 dBm (25 mW)</li> <li>• 11 dBm (12.5 mW)</li> <li>• 8 dBm (6.25 mW)</li> <li>• 5 dBm (3.13 mW)</li> <li>• 2 dBm (1.56 mW)</li> <li>• -1dBm (0.79mW)</li> </ul>
Frequency band and 20-MHz operating channels	<p>B (B regulatory domain):</p> <ul style="list-style-type: none"> <li>• 2.412 to 2.462 GHz; 11 channels</li> <li>• 5.180 to 5.320 GHz; 8 channels</li> <li>• 5.500 to 5.700 GHz; 11 channels</li> <li>• 5.745 to 5.865 GHz; 7 channels</li> </ul>

## Want to Buy

Get a Quote



[Learn More](#) about Hi-Network



[Search](#) our Resource Library



[Follow](#) us on LinkedIn



Contact for [Sales or Support](#)

## Contact HI-NETWORK.COM For Global Fast Shipping

HongKong Office Tel: +00852-66181601

HangZhou Office Tel: +0086-571-86729517

Email: [info@hi-network.com](mailto:info@hi-network.com)

Skype: echo.hinetwork

WhatsApp Business: +8618057156223